## **Digital IC Tester**



## **GUT-6000B**



(€

### **GUT-6600A**

#### **GUT-6000B FEATURES**

- \* Loop Test
- \* Auto-Search
- \* Self-Diagnosis
- \* Over-Load Protection
- \* Measures 1800 Types of Device
- \* 54/74 Series TTL
- \* 4000 and 4500 Series CMOS
- \* Test Socket: 28-Pin

#### **GUT-6600A FEATURES**

- \* Easy-Operation Tester, Particularly Designed for the Digital IC
- \* Supported Device: 74/54/40/45, Drive 2xxx
- \* Small, Portable, Light and Power-Saving
- \* Can be Operated using either DC adaptor or
- \* Average Search Time: 0.6 Second \* Display: 16 Characters in 1 Line LCD
- \* Test Pins: 14~24 Pins

The GUT-6000B is a desktop digital IC tester. Oriented toward automating testing tasks, the GUT-6000B contains high-end features such as auto-search and loop testing. Automated processes provide an intelligent and continuous process for detecting defective ICs. Self-diagnosis functions and over-load protection mechanisms make the GUT-6000B close to maintenance-free, releasing users from unnecessary hassles. The wide device coverage includes the 1800 series as well as the ubiquitous TTL and CMOS, providing a one-size fits-all solution for an IC testing bench area.

The GUT-6600A is a portable Digital IC tester with features matching those of its desktop cousin, the GUT-6000B. Standard DC adaptor operation or battery provides a secure power supply anytime, anywhere. Geared towards ease of use, no programming or fixtures are required when operating GUT-6600A; users simply have to plug in the device and a search is completed within a mere 0.6 seconds on average. All these features and compact profile make the GUT-6600A the ideal choice as an additional companion in a users' toolkit.

SPECIFICATIONS		CUT 4400
	GUT-6000B	GUT-6600A
TEST RANGE		
	TTL 74/54	TTL 74/54
	CMOS 40/45	CMOS 40/45
	DRIVE	DRIVE 2xxx
TEST VOLTAGE		
	2.5/3.0/3.3/5V	2.5/3.0/3.3/5V
TEST TIME		
	Average Search Time: 0.6Sec	Average Search Time : 0.6Sec
DISPLAY		
	16Characters in 1 line LCD	16 Characters in 1 line LCD
POWER SOURCE		
	AC100V~240V±10%,50/60Hz	DC 9V/500mA adaptor or 9V battery x 2(*)
DIMENSIONS & WEIGHT		
	335(W) ×105(H) ×300(D)mm, Approx. 1.5kg	110(W) x 45(H) x 160(D)mm, Approx. 0.4kg

(\*) Batteries not included

## ORDERING INFORMATION

GUT-6000B Digital IC Tester GUT-6600A Handy Digital IC Tester

#### ACCESSORIES:

User manual  $\times$  1 , Power cord  $\times$  1 (GUT-6000B) User manual x 1, DC 9V/500mA adaptor (GUT-6600A)

(Authorized Distributor)

# **Analytical Electronics Services Pvt. Ltd.**



B-76, G.I.D.C. Electronics Estate, Opp. Water Tank, Sector-25, GANDHINAGAR-382 024, Gujarat (INDIA) Tel: +79-(0)79-23287267, 29289167,

> Fax: +91-(0)79-23287266 E-mail: sales@analyticalelectronics.in, info@analyticalelectronics.in